



PARASNATH ELECTRONICS PVT. LTD.,
B-36/5, G.T.KARNAL ROAD INDUSTRIAL AREA, DELHI-110033

CIN No. U74899DL1995PTC073088

Ph.No. :- +91 11 45872116, 45872117, Mobile No. :- +91 9810096248, Email :- Info@proximityswitches.in

Inductive Proximity Switch

Model No.-----PE-IN-3-14A-N1-55-F

1. SIZE	: M-14X55 with M-12 separate amplifier
2. TYPE	: NPN
3. OUTPUT LOGIC	: NO
4. OPERATING VOLTAGE	: 5-40 VDC
5. MAX. LOAD CURREN	: 300 mAmp.
6. SENSING DISTANCE	: 3.0mm for standard object size
7. SWITCHING FREQUENCY	: 400 Hz.
8. VOLTAGE DROP AT FULL LOAD	: 2.5 VDC
9. NO LOAD CURRENT	: >10.0 mAmp.
10. RESIDUAL CURRENT	: 0.001 mAmp.
11. POSITION INDICATION	: LED
12. CABLE	: 3 core PVC & PU Flexible
13. H.V. TEST	: 1.5 KV for 1 Sec.
14. AMBIENT TEMP.	: 70° C
15. ENCLOSURE	: Nickel Platted Brass Tube
16. PROBE SIZE	: M-14x55
17. MOUNTING	: Flush Type
18. PROTECTION GRADE	: IP-67
19. APPROVALS	: CE
20. STANDARD OBJECT SIZE	: 15X15X1 mm



PARASNATH ELECTRONICS PVT. LTD.

Model no.-- PE-IN-3-14A-N1-55-F

Make----- PARAS

Dimenssions--- All Dim. in mm