



**PARASNATH ELECTRONICS PVT. LTD.,**  
**B-36/5, G.T.KARNAL ROAD INDUSTRIAL AREA, DELHI-110033**

CIN No. U74899DL1995PTC073088

Ph.No. :- +91 11 45872116, 45872117, Mobile No. :- +91 9810096248, Email :- Info@proximityswitches.in

## LDR Type Proximity Switch

Model No.-----PE-L-18-P1-50

- |                              |                            |
|------------------------------|----------------------------|
| 1. SIZE                      | : M-18X50                  |
| 2. TYPE                      | : PNP                      |
| 3. OUTPUT LOGIC              | : NO                       |
| 4. OPERATING VOLTAGE         | : 10-30 VDC                |
| 5. MAX. LOAD CURRENT         | : 200 mAmp.                |
| 6. SWITCHING FREQUENCY       | : 250 Hz.                  |
| 7. VOLTAGE DROP AT FULL LOAD | : 2.5 VDC                  |
| 8. NO LOAD CURRENT           | : >10.0 mAmp.              |
| 9. RESIDUAL CURRENT          | : 0.001 mAmp.              |
| 10. POSITION INDICATION      | : LED                      |
| 11. CABLE                    | : 3 core PVC & PU Flexible |
| 12. H.V. TEST                | : 1.5 KV for 1 Sec.        |
| 13. AMBIENT TEMP.            | : 70 <sup>0</sup> C        |
| 14. ENCLOSURE                | : Nickel Plated Brass Tube |
| 15. PROBE SIZE               | : M-18X50                  |
| 16. APPROVALS                | : CE                       |
| 17. STANDARD OBJECT SIZE     | : 20X20X1 mm               |



**PARASNATH ELECTRONICS PVT. LTD.**

**Model no.---- PE-L-18-P1-50**

**Make----- PARAS**

**Dimensions--- All Dim. in mm**