



PARASNATH ELECTRONICS PVT. LTD.,
B-36/5, G.T.KARNAL ROAD INDUSTRIAL AREA, DELHI-110033

CIN No. U74899DL1995PTC073088

Ph.No. :- +91 11 45872116, 45872117, Mobile No. :- +91 9810096248, Email :- Info@proximityswitches.in

Through Beam Type Photo Electric Proximity Switch with Controller

Model No.-----PE-10-F/N

- | | |
|--------------------------|--|
| 1. SIZE | : M-18 |
| 2. OUTPUT LOGIC | : NO |
| 3. OPERATING VOLTAGE | : 220-240 VAC |
| 4. MAX. LOAD CURRENT | : 6 Amp. Relay O/P |
| 5. SENSING DISTANCE | : 10 mtr. for standard object size |
| 6. SWITCHING FREQUENCY | : 100 Hz. |
| 7. POSITION INDICATION | : LED |
| 8. DELAY CIRCUIT | : Off Delay & On delay |
| 9. CABLE | : 3 core PVC & PU Flexible |
| 10. H.V. TEST | : 1.5 KV for 1 Sec. |
| 11. AMBIENT TEMP. | : 70° C |
| 12. ENCLOSURE | : Nickel Platted Brass Tube with Plastic Box |
| 13. PROBE SIZE | : 18 |
| 14. APPROVALS | : CE |
| 15. STANDARD OBJECT SIZE | : 20x20x1 |



PARASNATH ELECTRONICS PVT. LTD.

Model no.----- PE-10-N/F

Make----- PARAS

Dimensions--- All Dim. in mm