



**PARASNATH ELECTRONICS PVT. LTD.,  
B-36/5, G.T.KARNAL ROAD INDUSTRIAL AREA, DELHI-110033**

CIN No. U74899DL1995PTC073088

Ph.No. :- +91 11 45872116, 45872117, Mobile No. :- +91 9810096248, Email :- Info@proximityswitches.in

## Through Beam Type Photo Electric Proximity Switch with Controller

Model No.-----PE-25-I

- |                          |  |
|--------------------------|--|
| 1. SIZE                  | : M-18                                       |
| 2. OUTPUT LOGIC          | : NO   |
| 3. OPERATING VOLTAGE     | : 220-240 VAC                                |
| 4. MAX. LOAD CURRENT     | : 6 Amp. Relay O/P                           |
| 5. SENSING DISTANCE      | : 20-25 mtr. for standard object size        |
| 6. SWITCHING FREQUENCY   | : 100 Hz.                                    |
| 7. POSITION INDICATION   | : LED  |
| 8. DELAY CIRCUIT         | : Instant Delay                              |
| 9. CABLE                 | : 3 core PVC & PU Flexible                   |
| 10. H.V. TEST            | : 1.5 KV for 1 Sec.                          |
| 11. AMBIENT TEMP.        | : 70° C                                      |
| 12. ENCLOSURE            | : Nickel Platted Brass Tube with Plastic Box |
| 13. PROBE SIZE           | : 18   |
| 14. APPROVALS            | : CE   |
| 15. STANDARD OBJECT SIZE | : 20x20x1                                    |



**PARASNATH ELECTRONICS PVT. LTD.**

**Model no.----- PE-25-I**

**Make----- PARAS**

**Dimensions--- All Dim. in mm**