## PARAS

## PARASNATH

PARAS	
Inductive Proximit	v Switch
Model NoPE-4D-540-P2-	
SIZE	: R-12x50x60
TYPE	: PNP
OUTPUT LOGIC	: NC
OPERATING VOLTAGE	: 5-40 VDC
MAX. LOAD CURRENT	: 300 mAmp.
SENSING DISTANCE	: 3.0 mm for standard object size
SWITCHING FREQUENCY	: 450 Hz.
VOLTAGE DROP AT FULL LOAD	: 2.5 VDC
NO LOAD CURRENT	: >10.0 mAmp.
RESIDUAL CURRENT	: 0.001 mAmp.
POSITION INDICATION	: LED
CABLE	: 3 core PVC & PU Flexible
H.V. TEST	: 1.5 KV for 1 Sec.
AMBIENT TEMP.	: 70°C
ENCLOSURE	: Plastic
PROBE SIZE	: 12x50x60
PROTECTION GRADE	: IP-67
APPROVALS	: CE
STANDARDOBJECT SIZE	: 15X15X1 mm
CONTRACTOR .	
k	
I T	
	INDUCTIVE PHOAMITY BATCON Improvement
	The second secon
- LED	
ž	
35	
	PARASNATH ELECTRONICS Pvt. Ltd
	MODEL NO : - r-12x50x60 with cann
	Drawing NO : -
	Maka DADAS
	Make - PARAS
	Dimension :- All Dim in mm